

RY-PRO
STANDBY SET
TURAL GAS FUEL

SPV & SPH SERIES RESIDENTIAL AND SMALL BUSINESS
STANDBY GENERATOR SET. CONSULT OPTIONAL EQUIPMENT
FOR AUTOMATIC TRANSFER SWITCH, AND OTHER ITEMS FOR
SPECIFIC USE APPLICATIONS.

50 HERTZ

1 PHASE, 110/220 VOLT
3 PHASE, 220, 380, 415,

MODEL FOR SINGLE PH.	SPV-80-5		SPH-100-5		SPH-120-5		SPV-1	
	LPG	NAT. GAS	LPG	NAT. GAS	LPG	NAT. GAS	LPG	
USED	6.5	5.5	8.5	8.0	10.5	9.0	12.5	
W @ SINGLE PHASE								
V @ SINGLE PHASE	6.0	5.0	7.5	7.0	9.5	8.5	12.0	
IPS @ 110 VOLTS	54	46	68	64	86	76	108	
IPS @ 220 VOLTS	27	23	34	32	43	38	54	
IA @ 3 PHASE .8 P.F.	8.0	6.8	10.5	10.0	13.0	11.3	15.6	
IA @ 3 PHASE .8 P.F.	7.5	6.0	9.5	8.8	11.8	10.5	15.0	
V @ 3 PHASE .8 P.F.	6.0	5.0	7.5	7.0	9.5	8.5	12.0	
IPS @ 220 VOLT, 3Ø	20	16	24	23	31	28	39	
IPS @ 380 VOLT, 3Ø	11	9	14	13	18	16	22	
IPS @ 415 VOLT, 3Ø	10	8	13	12	16	15	20	
IPS @ 400 VOLT, 3Ø	11	9	13	13	17	15	21	
VANGUARD			HONDA			VANGUARD		
IG			AIR COOLED				LIQUID CO	
LATE HP RATING *	16 (11.5)	16 (9.5)	20 (16)	20 (15)	24 (19)	24 (17)	28 (22)	
NTIMETERS	480	480	614	614	670	670	952	
ERS	2	2	2	2	2	2	3	
ATION								
UFFLER								
% LOAD (FT³ /HR)	37	81	52	112	68	154	100	
% LOAD (FT³ /HR)	26	56	36	78	51	115	75	
E=67, O=70		E=66, O=69	E=69, O=75	E=68, O=74	E=71, O=77	E=70, O=76	E=70, O=76	
EGULATION			±5% VOLTAGE REGULATION				±1/2% VOLT. R	
EGULATION			5% FREQUENCY REGULATION ON ALL MODELS					
WAVEFORM (SINE-WAVE)			HARMONIC DISTORTION IS LIMITED TO JUST 7 % ON ALL SENTRY-PRO GENERATORS					
TELEPHONE INTERFERENCE FACTOR (TIF)			DISTORTION IS LIMITED TO JUST 250					
MOTOR START	1 HP	3/4 HP	2 1/2 HP	2 HP	3 1/2 HP	3 HP	5 HP	
OWNS								
REAKER								
IG START								
COOL DOWN								
ERY SIZE								
ATTERY CHARGER								
								</

ARD HOUSING Lbs	380	415	460	570
DARD HOUSING Lbs	430	465	510	620
S-SILENT HOUSING Lbs	405	440	485	615
R-SILENT HOUSING Lbs	450	490	535	665

S BATTERY IS NOT FURNISHED WITH THESE SENTRY-PRO GENERATORS. ALL DRY FUEL, (LPG AND NATURAL GAS) ENGINES HAVE CARBURETORS SET FOR 6 OUNCE FUEL PRE
 NOTIFY GILLETTE FOR SPECIAL CARBURETOR IF YOUR NATURAL GAS PRESSURE IS 4 OUNCE FUEL PRESSURE (7" WATER COLUMN). * ACTUAL ENGINE HP IS IN PARENTHESIS

GILLETTE GENERATORS, INC 1340 WADE DRIVE ELKHART, IN 46514 USA TEL. (574) 2
 WEB-SITE : <http://www.gillettegenerators.com> E-mail : sales@gillettegenerators.com FAX (574) 2